

# Integrated WizarSwitch IPC-11H

**Comm Integrated WizarSwitch (IPC Series) - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and displays.**

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

## Built-In Scalers, Selector and Splitters Functions.

Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.



## Built-In Scalers, Selector and Splitters Functions

## Features

- **Display Controller**  
Power ON/OFF, input source selections, volume control via RS232 Commands
- One Touch Selection with LED Back-Lit Indications
- INPUTS : 2 HDMI, 1 VGA, 3 USB
- OUTPUTS: 2 HDMI, 1 USB
- Built-In HDMI Selector and HDMI Splitter
- Digital Volume Control for sound level adjustments
- Digital Volume Control for MIC Inputs sound adjustments
- STANDBY mode - MIC Volume Control usable
- HDMI1 with Audio: PC Monitor is usable even Display (projector) is OFF
- 3 USB Connections

### SELECTOR SWITCH

(with LED Back-Lit Indications)

- Display ON / OFF
- FUNCTION (Blank / Freeze, HDMI Reset)
- Screen / Audio IN Selector
- Audio Selector for Mic and Source
- Screen (UP/DOWN)
- Audio Volume (UP / DOWN / MUTE) - for HDMI & VGA Audio
- HDMI 1 / USB 1 IN Selector
- HDMI 2 / USB 2 IN Selector
- VGA 3 / USB 3 IN Selector

## Specifications

### A) Input

- |                    |                               |
|--------------------|-------------------------------|
| • HDMI 1 / 2       | - HDMI with Audio Embedded    |
| • VGA Signal       | - VGA (D-Sub 15-Pin Female)   |
| • Audio Signal     | - 3.5mm Mini Jack Stereo      |
| • Microphone IN    | - 3.5mm Mini Jack x 2         |
| • USB 1 / 2 / 3 IN | - USB Female Type B Connector |

### B) Output

- |                |                          |
|----------------|--------------------------|
| • HDMI 1 / 2   | - Monitor OUT x 2        |
| • Audio Signal | - 3.5mm Mini Jack Stereo |
| • USB          |                          |

### C) Communication Control

- |                       |                              |
|-----------------------|------------------------------|
| • Serial Control Port | - RS232                      |
| • Baud Rate           | - 9600, 19200, 38400, 115200 |
| • Data / Stop Bits    | - 8 Bits / 1 Bits            |
|                       | No parity                    |

### D) Power

- DC 12V Power Adapter