

## Dual-Channel Wireless PA System

### CWR-1100W

Wireless PA System, suitable for a wide range of events - indoors and outdoors

- 160W max power output
- One-touch wireless frequency sync
- Bluetooth MP3 player with USB/TF
- Built-in UHF 16 Frequency Receiver
- Voice priority function
- ON/OFF Power switch to save power
- Come with battery and charging indicator
- Built-in Lithium Rechargeable Battery



Front View



Rear View

## Specifications

A) PA System	
Power Output	110W - 160W(max)
Speaker	10" Woofer Speaker, 1" Tweeter
Frequency Response	50Hz-18Khz ±3dB
Audio Input - Wired Mic	1 X MIC (1/4"), 1 X XLR
Audio Input - Line-in	1 X Line In (3.5mm), 2 X RCA
Line Output	2 X RCA
Voice Priority	Yes
Power Supply AC	15V 6A Power Adaptor
Power Supply DC & Battery	12V 7A Rechargeable Lead Acid Battery
Recharging Time	8 ~ 10 Hours
Operating Time (depends on usage)	6 ~ 8 Hours
Battery Indicator	Battery level with charging status
Dimensions	345 (L) x 343 (W) x 505 (H) mm
Weight	19.0 kg (includes battery)
Audio Player	Bluetooth MP3 player with USB/TF
B) Wireless Receiver	
Wireless Microphone - Option 1	<b>Model : CW5-H Handheld microphone x 2</b>
Wireless Microphone - Option 2	<b>Model : CW5-BC Lavalier mic with bodypack transmitter x 2</b>
Wireless Receiver Module	Dual Channel
Frequency Channel	UHF16 Frequency
Oscillation Mode	PLL Synthesized
Frequency Range	UHF 640 to 680 MHz
Receiving Sensitivity	-95dB
Spurious Emission	< 55dB
SNR Rate	> 95dB
Indicator	LED RF Signal
Wireless Mic RF Output Power	10mW



**CW5-H**  
Handheld microphone



**CW5-B**  
Bodypack transmitter