

Integrated Control Switches

IPC-3A

new model!



comm Integrated Control Switches (IPC Series) - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and plasma displays.

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

Built-In Signal Amplifiers of 250MHz / 350MHz bandwidths to minimise signal-loss worries. Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.

FEATURES

Display Controller for your Projector, Plasma (Power ON/OFF, input source selections, volume control) via RS232 Commands

One Touch Selection with LED Back-Lit Indications

32 sets of pre-programmed control protocols

Dip-Switch Settings Selections

Built-In Signal Amplifier of 350MHz

Digital Volume Control for sound level adjustments

* **Volume Maximum Indicator**

* **Video Source Selector Synchronize with Audio output**

* **Audio Source Selector Over-ride Video Selection**

* **PLUG & PLAY!** - EXTERNAL Output Connections

SELECTOR SWITCH

(with LED Back-Lit Indications)

- Display ON / OFF
- Volume UP / MUTE / DOWN (Digital)
- Source Selector (Switch between PC or Video Input)
- Audio Selector (Select from PC, Video, MIC Audio)
- Blank (Toggle Button)
- Auto Sync (Toggle Button)

SPECIFICATIONS

A) Input

- | | |
|---------------|----------------------------------|
| PC Signal | - VGA (D-Sub 15-Pin Female) |
| PC Audio | - 3.5mm Mini Jack |
| Video Signal | - Composite Video (RCA) |
| Audio Signal | - Stereo / Composite Audio (RCA) |
| Microphone IN | - 6.35mm Phono Jack |

B) Output

- | | |
|--------------|---------------------------------|
| PC Signal | - 2 x VGA (D-Sub 15-Pin Female) |
| | VGA Bandwidth of 350MHz |
| Video Signal | - Composite Video (RCA) |
| Audio Signal | - 3.5mm Mini Jack |
| RS232 | - Mini Jack |
| Microphone | - 14 steps to Maximum Volume |

C) Communication Control

- | | |
|--|------------------------------|
| Serial Control Port | - RS232 |
| Baud Rate | - 9600, 19200, 38400, 115200 |
| Data / Stop Bits | - 8 Bits / 1 Bits |
| | No parity |
| Pre-programmed 32 sets of control protocols; | |
| - Selection through Dip-Switch Setting | |

D) Power

DC 12V Power Adapter

All products information and specifications are subject to changes without prior notice.