

## 4-Channel Wireless PA System CWR-103

High Performance Wireless PA System, suitable for a wide range of events - indoors and outdoors

- 450W max power output
- One-touch wireless frequency sync
- Bluetooth MP3 player with USB/SD
- Built-in UHF 16 Frequency Receiver
- Voice priority function
- ON/OFF Power switch to save power
- Come with battery and charging indicator
- Built-in Lithium Rechargeable Battery
- Built-in Retractable handle and wheels



Front View



Rear View

## Specifications

A) PA System	
Power Output	320W - 450W(max)
Speaker	12" Woofer Speaker, 1" Tweeter
Frequency Response	50Hz-18Khz ±3dB
Audio Input - Wired Mic	1 X MIC (1/4"), 2 X XLR
Audio Input - Line-in	1 X Line In (3.5mm), 2 X RCA
Line Output	6.3mm
Voice Priority	Yes
Power Supply AC	AC Cord / Power Adaptor
Power Supply DC & Battery	25.2V 8A Rechargeable Lead Acid Battery
Recharging Time	10 ~ 12 Hours
Operating Time (depends on usage)	8 ~ 10 Hours
Battery Indicator	Battery level with charging status
Dimensions	410 (L) x 360 (W) x 580 (H) mm
Weight	22.0 kg (includes battery)
Audio Player	Bluetooth MP3 player with USB/SD
B) Wireless Receiver	
Wireless Microphone - Option 1	<b>Model : CW5-H Handheld microphone x 2</b>
Wireless Microphone - Option 2	<b>Model : CW5-BC Lavalier mic with bodypack transmitter x 2</b>
Wireless Receiver Module	4 Channels
Frequency Channel	UHF16 Frequency
Oscillation Mode	PLL Synthesized
Frequency Range	UHF 640 to 680 MHz
Receiving Sensitivity	-95dB
Spurious Emission	< 55dB
SNR Rate	> 95dB
Indicator	LED RF Signal
Wireless Mic RF Output Power	10mW



**CW5-H**  
Handheld microphone



**CW5-B**  
Bodypack transmitter

All products information and specifications are subject to changes without prior notice.