

Integrated WizarSwitch

IPC-8+

Comm Integrated WizarSwitch (IPC Series) - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and displays.

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

Built-In HDMI Selector and Splitters Functions.

Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.



**With
Built-in
HDMI Selector
and
Splitter Functions**

Features

- **Display Controller**
Power ON/OFF, input source selections, volume control via RS232 Commands
- One Touch Selection with LED Back-Lit Indications
- INPUTS : 2 HDMI, 3 USB, 1 VGA
- OUTPUTS: 2 HDMI, 2 USB, 1 VGA
- Digital Volume Control for sound level adjustments
- Volume Control Knob for MIC Inputs sound adjustments
- STANDBY mode - MIC Volume Control usable
- HDMI1 with Audio: PC Monitor is usable even when Projector is OFF
- **3 USB Connections**

SELECTOR SWITCH

(with LED Back-Lit Indications)

- Display ON / OFF
- FUNCTION (Blank / Sync)
- Screen / Audio Volume (UP / DOWN)
- Screen / Audio IN Selector
- HDMI 1 / USB 1 IN Selector
- HDMI 2 / USB 2 IN Selector
- PC / USB 2/ WIRELESS Selector
- RESET for HDMI

Specifications

A) Input

- HDMI 1 / 2 - HDMI with Audio Embedded
- PC Signal - VGA (D-Sub 15-Pin Female)
- PC Audio - 3.5mm Mini Jack
- Microphone IN - 3.5mm Mini Jack
- USB 1 / 2 IN - USB Female Type B Connector
- USB IN - USB Female Type A Connector

B) Output

- HDMI - HDMI
- HDMI - Monitor OUT
- PC Signal
- Audio Signal
- Microphone OUT

C) Communication Control

- Serial Control Port - RS232
- Baud Rate - 9600, 19200, 38400, 115200
- Data / Stop Bits - 8 Bits / 1 Bits
No parity

D) Power

- DC 12V Power Adapter

All products information and specifications are subject to changes without prior notice.